

$$N = \int_{\mathcal{A}} \sigma_{zz} dA$$


$$Q_y = \int_{\mathcal{A}} \tau_{yz} dA$$

$$Q_x = \int_{\mathcal{A}} \tau_{zx} dA$$

$$M_x \equiv M_{(G,x)} = \int_{\mathcal{A}} \sigma_{zz} y dA$$

$$M_y \equiv M_{(G,y)} = - \int_{\mathcal{A}} \sigma_{zz} x dA$$

$$M_t \equiv M_{(C,z)} = \int_{\mathcal{A}} [\tau_{yz}(x - x_C) - \tau_{zx}(y - y_C)] dA$$







Figure 1: An overview of symmetrical and skew-symmetrical (generalized) loading and displacements.



$$\epsilon_z = a + bx + cy \quad (1)$$

$$\frac{d\theta}{dz} = \frac{1}{\rho_x}, \quad \theta = -\frac{dv}{dz}, \quad \frac{d^2v}{dz^2} = -\frac{1}{\rho_x} \quad (2)$$


$$\frac{d\phi}{dz} = \frac{1}{\rho_y}, \quad \phi = +\frac{du}{dz}, \quad \frac{d^2u}{dz^2} = +\frac{1}{\rho_y} \quad (3)$$

$$\sigma_z = E_z \epsilon_z = E_z \left(\bar{\epsilon} - \frac{1}{\rho_y} x + \frac{1}{\rho_x} y \right) \quad (4)$$

$$N = \iint_{\mathcal{A}} E_z \epsilon_z dA = \overline{E} \overline{A} \bar{\epsilon} \quad (5)$$

$$M_x = \iint_{\mathcal{A}} E_z \epsilon_z y dA = \overline{E} \overline{J}_{xx} \frac{1}{\rho_x} - \overline{E} \overline{J}_{xy} \frac{1}{\rho_y} \quad (6)$$

$$M_y = - \iint_{\mathcal{A}} E_z \epsilon_z x dA = -\overline{E} \overline{J}_{xy} \frac{1}{\rho_x} + \overline{E} \overline{J}_{yy} \frac{1}{\rho_y} \quad (7)$$



$$\overline{EA} = \iint_{\mathcal{A}} E_z(x, y) dA \quad (8)$$

$$\overline{EJ}_{xx} = \iint_{\mathcal{A}} E_z(x, y) yy dA \quad (9)$$

$$\overline{EJ}_{xy} = \iint_{\mathcal{A}} E_z(x, y) yx dA \quad (10)$$

$$\overline{EJ}_{yy} = \iint_{\mathcal{A}} E_z(x, y) xx dA \quad (11)$$

$$\bar{\epsilon} = \frac{N}{\overline{EA}}. \quad (12)$$



$$\frac{1}{\rho_x} = \frac{M_x \overline{EJ}_{yy} + M_y \overline{EJ}_{xy}}{\overline{EJ}_{xx} \overline{EJ}_{yy} - \overline{EJ}_{xy}^2} \quad (13)$$

$$\frac{1}{\rho_y} = \frac{M_x \overline{EJ}_{xy} + M_y \overline{EJ}_{xx}}{\overline{EJ}_{xx} \overline{EJ}_{yy} - \overline{EJ}_{xy}^2} \quad (14)$$

$$\frac{1}{\rho_{eq}} = \sqrt{\frac{1}{\rho_x^2} + \frac{1}{\rho_y^2}} \quad (15)$$

$$\sigma_z = E_z \epsilon_z \quad (16)$$

$$= \alpha M_x + \beta M_y + \gamma N \quad (17)$$



$$\alpha(x, y, E_z, \overline{EJ}_{**}) = E_z(x, y) \frac{-\overline{EJ}_{xy}x + \overline{EJ}_{yy}y}{\overline{EJ}_{xx}\overline{EJ}_{yy} - \overline{EJ}_{xy}^2} \quad (18)$$

$$\beta(x, y, E_z, \overline{EJ}_{**}) = E_z(x, y) \frac{-\overline{EJ}_{xx}x + \overline{EJ}_{xy}y}{\overline{EJ}_{xx}\overline{EJ}_{yy} - \overline{EJ}_{xy}^2} \quad (19)$$



$$\gamma(x, y, E_z, \overline{EA}) = E_z(x, y) \frac{1}{\overline{EA}}. \quad (20)$$




$$(x_N, y_N) \equiv \left(\frac{\bar{e}\rho_x^2\rho_y}{\rho_x^2 + \rho_y^2}, -\frac{\bar{e}\rho_x\rho_y^2}{\rho_x^2 + \rho_y^2} \right);$$

$$\hat{n}_\parallel = \sqrt{\rho_x^2 + \rho_y^2} \left(\frac{1}{\rho_x}, \frac{1}{\rho_y} \right),$$

$$\hat{n}_\perp = \sqrt{\rho_x^2 + \rho_y^2} \left(-\frac{1}{\rho_y}, \frac{1}{\rho_x} \right),$$

$$\lambda \begin{bmatrix} M_x \\ M_y \end{bmatrix} = \begin{bmatrix} \frac{1}{\rho_x} \\ \frac{1}{\rho_y} \end{bmatrix} = \underbrace{\frac{1}{\overline{EJ}_{xx}\overline{EJ}_{yy} - \overline{EJ}_{xy}^2} \begin{bmatrix} \overline{EJ}_{yy} & \overline{EJ}_{xy} \\ \overline{EJ}_{xy} & \overline{EJ}_{xx} \end{bmatrix}}_{[\overline{EJ}]} \begin{bmatrix} M_x \\ M_y \end{bmatrix} \quad (21)$$





$$S_y = \frac{dM_x}{dz}, \quad S_x = -\frac{dM_y}{dz}, \quad (22)$$

$$\frac{d\sigma_z}{dz} = \alpha(x, y, E_z, \overline{EJ}_{**}) S_y - \beta(x, y, E_z, \overline{EJ}_{**}) S_x \quad (23)$$

$$\frac{d\tau_{zx}}{dx} + \frac{d\tau_{yz}}{dy} + \frac{d\sigma_z}{dz} + q_z = 0 \quad (24)$$

$$\bar{\tau}_{zi}t = \int_{A^*} \frac{d\sigma_z}{dz} dA, \quad (25)$$



$$\bar{\tau}_{zi} = \frac{1}{t} \int_t \tau_{zi} dr \quad (26)$$


$$\bar{\tau}_{zi}t = \int_{A^*} \left(\frac{yS_y}{J_{xx}} + \frac{xS_x}{J_{yy}} \right) dA = \frac{\bar{y}^* A^*}{J_{xx}} S_y + \frac{\bar{x}^* A^*}{J_{yy}} S_x, \quad (27)$$



$$\bar{\tau}_{zi}t = q_{zi} = \int_0^s \int_{-t/2}^{t/2} \frac{d\sigma_z}{dz} dr d\varsigma \approx \int_0^s \frac{d\sigma_z}{dz} \Big|_{r=0} t d\varsigma. \quad (28)$$

$$\bar{\tau}_{zi}(s)t(s) = q(s) = \int_a^s \frac{d\sigma_z}{dz} t d\varsigma + \underbrace{\bar{\tau}_{zi}(a)t(a)}_{q_A}. \quad (29)$$

$$\tau(s) = \frac{S_1}{\mathcal{A}} f_{;S1}(s) + \frac{S_2}{\mathcal{A}} f_{;S2}(s) + \tau_A f_{;A}(s) + \tau_B f_{;B}(s) \quad (30)$$











$$\Delta U = \int_s \frac{\tau^2}{2G_{sz}} t \Delta z ds \quad (31)$$

$$\frac{\partial \Delta U}{\partial \bar{\tau}_i} = \bar{\delta}_i t \Delta z \quad (32)$$







$$K_t = \frac{4A^2}{\oint \frac{1}{t} dl} \quad (33)$$

$$\tau_{\max} = \frac{M_t}{2t_{\min} A} \quad (34)$$

$$K_T \approx \frac{1}{3} \int_0^l t^3(s) ds \quad (35)$$

$$K_T \approx \frac{1}{3} \sum_i l_i t_i^3 \quad (36)$$

$$\tau_{\max} = \frac{M_t t_{\max}}{K_T} \quad (37)$$





$$q_i = \frac{\partial U}{\partial Q_i}$$

$$\frac{dU}{dl} = \frac{1}{2} \begin{pmatrix} N \\ M_x \\ M_y \\ Q_x \\ Q_y \\ M_t \end{pmatrix}^\top \begin{pmatrix} a_{1,1} & g_{1,2} & g_{1,3} & i_{1,4} & i_{1,5} & i_{1,6} \\ 0 & b_{2,2} & e_{2,3} & i_{2,4} & i_{2,5} & i_{2,6} \\ 0 & 0 & b_{3,3} & i_{3,4} & i_{3,5} & i_{3,6} \\ 0 & 0 & 0 & c_{4,4} & f_{4,5} & h_{4,6} \\ 0 & 0 & 0 & 0 & c_{5,5} & h_{5,6} \\ 0 & 0 & 0 & 0 & 0 & d_{6,6} \end{pmatrix} \begin{pmatrix} N \\ M_x \\ M_y \\ Q_x \\ Q_y \\ M_t \end{pmatrix}, \quad (38)$$

$$a_{1,1} = \frac{1}{EA} \quad \{b_{2,2}, b_{3,3}, e_{2,3}\} = \frac{\{J_{yy}, J_{xx}, 2J_{xy}\}}{E(J_{xx}J_{yy} - J_{xy}^2)}$$

$$d_{6,6} = \frac{1}{GK_t} \quad \{c_{4,4}, c_{5,5}, f_{4,5}\} = \frac{\{\chi_x, \chi_y, \chi_{xy}\}}{GA},$$



$$\begin{aligned} u_P &= u + z(1 + \check{\epsilon}_z) \frac{\cos \theta}{\sqrt{1 - \sin^2 \phi \sin^2 \theta}} \sin \phi \\ v_P &= v - z(1 + \check{\epsilon}_z) \frac{\cos \phi}{\sqrt{1 - \sin^2 \phi \sin^2 \theta}} \sin \theta \\ w_P &= w + z \left((1 + \check{\epsilon}_z) \frac{\cos \phi \cos \theta}{\sqrt{1 - \sin^2 \phi \sin^2 \theta}} - 1 \right), \end{aligned}$$

$$\begin{aligned} \check{\epsilon}_z(z) &= \frac{1}{z} \int_0^z \epsilon_z d\varsigma \\ &= \frac{1}{z} \int_0^z -\frac{\nu}{1-\nu} (\epsilon_x + \epsilon_y) d\varsigma, \end{aligned}$$

$$u_P = u + z\phi \quad (39)$$

$$v_P = v - z\theta \quad (40)$$

$$w_P = w. \quad (41)$$

$$\frac{\partial w}{\partial x} = \bar{\gamma}_{zx} - \phi \quad (42)$$

$$\frac{\partial w}{\partial y} = \bar{\gamma}_{yz} + \theta \quad (43)$$



$$\epsilon_x = \frac{\partial u_P}{\partial x} = \frac{\partial u}{\partial x} + z \frac{\partial \phi}{\partial x} \quad (44)$$



$$\epsilon_y = \frac{\partial v_P}{\partial y} = \frac{\partial v}{\partial y} - z \frac{\partial \theta}{\partial y} \quad (45)$$

$$\gamma_{xy} = \frac{\partial u_P}{\partial y} + \frac{\partial v_P}{\partial x} \quad (46)$$

$$= \left(\frac{\partial u}{\partial y} + \frac{\partial v}{\partial x} \right) + z \left(+ \frac{\partial \phi}{\partial y} - \frac{\partial \theta}{\partial x} \right) \quad (47)$$

$$\underline{e} = \begin{bmatrix} \frac{\partial u}{\partial x} \\ \frac{\partial v}{\partial y} \\ \frac{\partial u}{\partial y} + \frac{\partial v}{\partial x} \end{bmatrix} = \begin{bmatrix} e_x \\ e_y \\ g_{xy} \end{bmatrix} \equiv \underline{\epsilon}_Q \quad (48)$$





$$\underline{\kappa} = \begin{bmatrix} +\frac{\partial\phi}{\partial x} \\ -\frac{\partial\theta}{\partial y} \\ +\frac{\partial\phi}{\partial y} - \frac{\partial\theta}{\partial x} \end{bmatrix} = \begin{bmatrix} \kappa_x \\ \kappa_y \\ \kappa_{xy} \end{bmatrix} \quad (49)$$

$$\underline{\epsilon}_P \equiv \underline{\epsilon} = \underline{\epsilon}_e + z \underline{\kappa}. \quad (50)$$

$$\begin{bmatrix} \sigma_x \\ \sigma_y \\ \tau_{xy} \end{bmatrix} = \underline{\sigma} = \underline{\underline{D}} \underline{\epsilon} = \underline{\underline{D}} \underline{\epsilon}_e + z \underline{\underline{D}} \underline{\kappa}, \quad (51)$$

$$\underline{\underline{D}} = \frac{E}{1-\nu^2} \begin{bmatrix} 1 & \nu & 0 \\ \nu & 1 & 0 \\ 0 & 0 & \frac{1-\nu}{2} \end{bmatrix}, \quad (52)$$



$$\epsilon_z = -\frac{\nu}{1-\nu} (\epsilon_x + \epsilon_y). \quad (53)$$



$$\begin{aligned} \underline{\underline{q}} &= \begin{bmatrix} q_x \\ q_y \\ q_{xy} \end{bmatrix} = \int_h \underline{\sigma} dz \\ &= \underbrace{\int_h \underline{\underline{D}} dz}_{\underline{\underline{a}}} \underline{\epsilon}_e + \underbrace{\int_h \underline{\underline{D}} z dz}_{\underline{\underline{b}}} \underline{\kappa} \end{aligned} \quad (54)$$

$$\underline{\underline{q}}_z = \begin{bmatrix} q_{xz} \\ q_{yz} \end{bmatrix} \quad q_{xz} = \int_h \tau_{zx} dz \quad q_{yz} = \int_h \tau_{yz} dz. \quad (55)$$

$$\begin{aligned} \underline{\underline{m}} &= \begin{bmatrix} m_x \\ m_y \\ m_{xy} \end{bmatrix} = \int_h \underline{\sigma} z dz \\ &= \underbrace{\int_h \underline{\underline{D}} z dz}_{\underline{\underline{b}} \equiv \underline{\underline{b}}^T} \underline{\epsilon}_e + \underbrace{\int_h \underline{\underline{D}} z^2 dz}_{\underline{\underline{c}}} \underline{\kappa}. \end{aligned} \quad (56)$$

$$\begin{bmatrix} \underline{\underline{q}} \\ \underline{\underline{m}} \end{bmatrix} = \begin{bmatrix} \underline{\underline{a}} & \underline{\underline{b}} \\ \underline{\underline{b}}^T & \underline{\underline{c}} \end{bmatrix} \begin{bmatrix} \underline{\epsilon}_e \\ \underline{\kappa} \end{bmatrix} \quad (57)$$





$$v^\dagger = \frac{1}{2} \begin{bmatrix} \underline{q} \\ \underline{m} \end{bmatrix}^\top \begin{bmatrix} \underline{e} \\ \underline{\kappa} \end{bmatrix} \quad (58)$$

$$= \frac{1}{2} \begin{bmatrix} \underline{e} \\ \underline{\kappa} \end{bmatrix}^\top \begin{bmatrix} \underline{a} & \underline{b} \\ \underline{\underline{b}}^T & \underline{\underline{c}} \end{bmatrix} \begin{bmatrix} \underline{e} \\ \underline{\kappa} \end{bmatrix}. \quad (59)$$

$$\underline{\underline{a}} = h \underline{\underline{D}} \quad \underline{\underline{b}} = \underline{\underline{0}} \quad \underline{\underline{c}} = \frac{h^3}{12} \underline{\underline{D}},$$

$$\underline{\gamma}_z = \begin{bmatrix} \bar{\gamma}_{yz} \\ \bar{\gamma}_{zx} \end{bmatrix}$$

$$\underline{q}_z = \begin{bmatrix} q_{xz} \\ q_{yz} \end{bmatrix}$$

$$v^\ddagger = \frac{1}{2} \underline{q}_z^\top \underline{\gamma}_z = \frac{1}{2} q_{xz} \bar{\gamma}_{xz} + \frac{1}{2} q_{yz} \bar{\gamma}_{yz}. \quad (60)$$

$$v^\ddagger = \frac{1}{2} \underline{\gamma}_z^\top \underbrace{\chi \int_h \underline{\underline{G}} dz}_{\underline{\Gamma}} \underline{\gamma}_z \quad (61)$$

$$\underline{q}_z = \underline{\underline{G}} \underline{\gamma}_z. \quad (62)$$



$$\underline{\underline{G}} = \frac{E}{2(1+\nu)} \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix},$$



$$\tau_{zx}(z) = - \int_{-\frac{h}{2}+o}^z \frac{\partial \sigma_x}{\partial x} + \frac{\partial \tau_{xy}}{\partial y} dz \quad (63)$$

$$\tau_{yz}(z) = - \int_{-\frac{h}{2}+o}^z \frac{\partial \tau_{xy}}{\partial x} + \frac{\partial \sigma_y}{\partial y} dz. \quad (64)$$

$$\underline{\underline{D}}_{123} = \begin{bmatrix} \frac{E_1}{1-\nu_{12}\nu_{21}} & \frac{\nu_{21}E_1}{1-\nu_{12}\nu_{21}} & 0 \\ \frac{\nu_{12}E_2}{1-\nu_{12}\nu_{21}} & \frac{E_2}{1-\nu_{12}\nu_{21}} & 0 \\ 0 & 0 & G_{12} \end{bmatrix} \quad (65)$$

$$\begin{bmatrix} \sigma_1 \\ \sigma_2 \\ \tau_{12} \end{bmatrix} = \underline{\underline{T}}_1 \begin{bmatrix} \sigma_x \\ \sigma_y \\ \tau_{xy} \end{bmatrix} \quad \begin{bmatrix} \epsilon_1 \\ \epsilon_2 \\ \gamma_{12} \end{bmatrix} = \underline{\underline{T}}_2 \begin{bmatrix} \epsilon_x \\ \epsilon_y \\ \gamma_{xy} \end{bmatrix} \quad (66)$$





$$\underline{\underline{T}}_1 = \begin{bmatrix} m^2 & n^2 & 2mn \\ n^2 & m^2 & -2mn \\ -mn & mn & m^2 - n^2 \end{bmatrix} \quad (67)$$

$$\underline{\underline{T}}_2 = \begin{bmatrix} m^2 & n^2 & mn \\ n^2 & m^2 & -mn \\ -2mn & 2mn & m^2 - n^2 \end{bmatrix} \quad (68)$$

$$m = \cos(\alpha) \quad n = \sin(\alpha) \quad (69)$$

$$\underline{\underline{T}}_1^{-1}(+\alpha) = \underline{\underline{T}}_1(-\alpha) \quad \underline{\underline{T}}_2^{-1}(+\alpha) = \underline{\underline{T}}_2(-\alpha) \quad (70)$$

$$\underline{\sigma} = \underline{\underline{D}} \epsilon \quad \underline{\underline{D}} \equiv \underline{\underline{D}}_{xyz} = \underline{\underline{T}}_1^{-1} \underline{\underline{D}}_{123} \underline{\underline{T}}_2 \quad (71)$$

$$\underline{\underline{G}} = \begin{bmatrix} n^2 G_{z1} + m^2 G_{2z} & mn G_{z1} - mn G_{2z} \\ mn G_{z1} - mn G_{2z} & m^2 G_{z1} + n^2 G_{2z} \end{bmatrix}.$$

$$k_x^* = \frac{12Fl}{Ebh^3} \quad (72)$$



$$m_x = m_x^* \quad m_y = 0 \quad \kappa_x = k_x^* \quad \kappa_y = -\nu k_x^*,$$



$$m_x = m_x^* \quad m_y = \nu m_x^* \quad \kappa_x = (1 - \nu^2) k_x^* \quad \kappa_y = 0.$$

$$g(y) \geq 0 \quad (73)$$

$$f(y) \geq 0 \quad (74)$$

$$g(y) \cdot f(y) = 0, \quad (75)$$





$$f(\xi, \eta) \stackrel{\text{def}}{=} \sum_i N_i(\xi, \eta) f_i \quad (76)$$

$$N_i(\xi, \eta) \stackrel{\text{def}}{=} \frac{1}{4} (1 \pm \xi) (1 \pm \eta), \quad (77)$$

$$\frac{\partial f}{\partial \xi} = \underbrace{\left(\frac{f_2 - f_1}{2} \right)}_{[\Delta f / \Delta \xi]_{12}} \underbrace{\left(\frac{1 - \eta}{2} \right)}_{N_1 + N_2} + \underbrace{\left(\frac{f_3 - f_4}{2} \right)}_{[\Delta f / \Delta \xi]_{43}} \underbrace{\left(\frac{1 + \eta}{2} \right)}_{N_4 + N_3} = a\eta + b \quad (78)$$

$$\frac{\partial f}{\partial \eta} = \left(\frac{f_4 - f_1}{2} \right) \left(\frac{1 - \xi}{2} \right) + \left(\frac{f_3 - f_2}{2} \right) \left(\frac{1 + \xi}{2} \right) = c\xi + d. \quad (79)$$

$$f(\xi, \eta) = [N_1(\xi, \eta) \quad \cdots \quad N_i(\xi, \eta) \quad \cdots \quad N_n(\xi, \eta)] \begin{bmatrix} f_1 \\ \vdots \\ f_i \\ \vdots \\ f_n \end{bmatrix} \\ = \underline{\underline{N}}(\xi, \eta) \underline{f}, \quad (80)$$



$$\underline{x}(\underline{\xi}) = \underline{\underline{m}}(\underline{\xi}) = \sum_{i=1}^4 N_i(\underline{\xi}) \underline{x}_i, \quad (81)$$



$$\underline{\underline{m}}(\underline{\xi}) = \begin{bmatrix} x(\xi, \eta) \\ y(\xi, \eta) \end{bmatrix}$$

$$x(\xi, \eta) = \sum_{i=1}^4 N_i(\xi, \eta) x_i \quad y(\xi, \eta) = \sum_{i=1}^4 N_i(\xi, \eta) y_i.$$

$$f(\xi, \eta) \stackrel{\text{def}}{=} \sum_i N_i(\xi, \eta) f_i \quad (82)$$

$$\begin{bmatrix} \frac{\partial f}{\partial \xi} \\ \frac{\partial f}{\partial \eta} \end{bmatrix} = \underbrace{\begin{bmatrix} \frac{\partial x}{\partial \xi} & \frac{\partial y}{\partial \xi} \\ \frac{\partial x}{\partial \eta} & \frac{\partial y}{\partial \eta} \end{bmatrix}}_{\underline{\underline{J}}^\top(\xi, \eta; \underline{x}_i)} \begin{bmatrix} \frac{\partial f}{\partial x} \\ \frac{\partial f}{\partial y} \end{bmatrix} \quad (83)$$





$$\begin{bmatrix} \frac{\partial f}{\partial \xi} \\ \frac{\partial f}{\partial \eta} \end{bmatrix} = \sum_i \begin{bmatrix} \frac{\partial N_i}{\partial \xi} \\ \frac{\partial N_i}{\partial \eta} \end{bmatrix} f_i. \quad (84)$$

$$\underline{\underline{J}}^\top(\xi, \eta) = \begin{bmatrix} \frac{\partial x}{\partial \xi} & \frac{\partial y}{\partial \xi} \\ \frac{\partial x}{\partial \eta} & \frac{\partial y}{\partial \eta} \end{bmatrix} \quad (85)$$

$$= \sum_i \left(\begin{bmatrix} \frac{\partial N_i}{\partial \xi} & 0 \\ \frac{\partial N_i}{\partial \eta} & 0 \end{bmatrix} x_i + \begin{bmatrix} 0 & \frac{\partial N_i}{\partial \xi} \\ 0 & \frac{\partial N_i}{\partial \eta} \end{bmatrix} y_i \right) \quad (86)$$

$$\begin{bmatrix} \frac{\partial f}{\partial x} \\ \frac{\partial f}{\partial y} \end{bmatrix} = (\underline{\underline{J}}^\top)^{-1} \begin{bmatrix} \cdots & \frac{\partial N_i}{\partial \xi} & \cdots \\ \cdots & \frac{\partial N_i}{\partial \eta} & \cdots \end{bmatrix} \begin{bmatrix} \vdots \\ f_i \\ \vdots \end{bmatrix} \quad (87)$$

$$= \underbrace{(\underline{\underline{J}}^\top)^{-1} \begin{bmatrix} \frac{\partial \underline{N}}{\partial \xi} \\ \frac{\partial \underline{N}}{\partial \eta} \end{bmatrix}}_{\underline{\underline{L}}(\xi, \eta; \underline{x}_i), \text{ or just } \underline{\underline{L}}(\xi, \eta)} \quad \text{f} \quad (88)$$

$$\int_{-1}^1 f(\xi) d\xi \approx \sum_{i=1}^n f(\xi_i) w_i; \quad (89)$$

$$p(\xi) \stackrel{\text{def}}{=} a_m \xi^m + a_{m-1} \xi^{m-1} + \dots + a_1 \xi + a_0$$



$$\int_{-1}^1 p(\xi) d\xi = \sum_{j=0}^m \frac{(-1)^j + 1}{j+1} a_j$$



$$r(a_j, (\xi_i, w_i)) \stackrel{\text{def}}{=} \sum_{i=1}^n p(\xi_i) w_i - \int_{-1}^1 p(\xi) d\xi \quad (90)$$

$$\left\{ \frac{\partial r(a_j, (\xi_i, w_i))}{\partial a_j} = 0, \quad j = 0 \dots m \right. \quad (91)$$

$$\int_a^b g(x) dx = \int_{-1}^1 g(m(\xi)) \frac{dm}{d\xi} d\xi \approx \sum_{i=1}^n g(m(\xi_i)) \left. \frac{dm}{d\xi} \right|_{\xi=\xi_i} w_i. \quad (92)$$

$$m(x) = \underbrace{\left(\frac{1-\xi}{2} \right)}_{N_1} a + \underbrace{\left(\frac{1+\xi}{2} \right)}_{N_2} b.$$





$$\frac{dm}{d\xi} = \frac{dN_1}{d\xi}a + \frac{dN_2}{d\xi}b = \frac{b-a}{2}$$

$$\int_a^b g(x)dx \approx \frac{b-a}{2} \sum_{i=1}^n g\left(\frac{b+a}{2} + \frac{b-a}{2}\xi_i\right) w_i. \quad (93)$$

$$\int_{-1}^1 \int_{-1}^1 f(\xi, \eta) d\xi d\eta \approx \sum_{i=1}^p \sum_{j=1}^q f(\xi_i, \eta_j) w_i w_j \quad (94)$$

$$\int_{-1}^1 \int_{-1}^1 f(\xi, \eta) d\xi d\eta \approx \sum_{l=1}^{pq} f(\underline{\xi}_l) w_l \quad (95)$$



$$\underline{\xi}_l = (\xi_i, \eta_j), \quad w_l = w_i w_j, \quad l = 1 \dots pq \quad (96)$$



$$dA_{xy} = \frac{1}{2!} \begin{vmatrix} 1 & x(\xi_P, \eta_P) & y(\xi_P, \eta_P) \\ 1 & x(\xi_P + d\xi, \eta_P) & y(\xi_P + d\xi, \eta_P) \\ 1 & x(\xi_P + d\xi, \eta_P + d\eta) & y(\xi_P + d\xi, \eta_P + d\eta) \end{vmatrix} + \\ + \frac{1}{2!} \begin{vmatrix} 1 & x(\xi_P + d\xi, \eta_P + d\eta) & y(\xi_P + d\xi, \eta_P + d\eta) \\ 1 & x(\xi_P, \eta_P + d\eta) & y(\xi_P, \eta_P + d\eta) \\ 1 & x(\xi_P, \eta_P) & y(\xi_P, \eta_P) \end{vmatrix}. \quad (97)$$

$$\mathcal{A} = \frac{1}{2!} \begin{vmatrix} 1 & x_1 & y_1 \\ 1 & x_2 & y_2 \\ 1 & x_3 & y_3 \end{vmatrix}, \quad \mathcal{H} = \frac{1}{n!} \begin{vmatrix} 1 & \underline{x}_1 \\ 1 & \underline{x}_2 \\ \vdots & \vdots \\ 1 & \underline{x}_{n+1} \end{vmatrix} \quad (98)$$

$$dA_{xy} \approx \frac{1}{2!} \begin{vmatrix} 1 & x & y \\ 1 & x + x_{,\xi}d\xi & y + y_{,\xi}d\xi \\ 1 & x + x_{,\xi}d\xi + x_{,\eta}d\eta & y + y_{,\xi}d\xi + y_{,\eta}d\eta \end{vmatrix} + \\ + \frac{1}{2!} \begin{vmatrix} 1 & x + x_{,\xi}d\xi + x_{,\eta}d\eta & y + y_{,\xi}d\xi + y_{,\eta}d\eta \\ 1 & x + x_{,\eta}d\eta & y + y_{,\eta}d\eta \\ 1 & x & y \end{vmatrix}$$

$$dA_{xy} = \frac{1}{2} \begin{vmatrix} 1 & x & y \\ 0 & x_{,\xi} & y_{,\xi} \\ 0 & x_{,\eta} & y_{,\eta} \end{vmatrix} d\xi d\eta + \frac{1}{2} \begin{vmatrix} 0 & x_{,\xi} & y_{,\xi} \\ 0 & x_{,\eta} & y_{,\eta} \\ 1 & x & y \end{vmatrix} d\xi d\eta$$









$$dA_{xy} = \frac{1}{2} \begin{vmatrix} x_{,\xi} & y_{,\xi} \\ x_{,\eta} & y_{,\eta} \end{vmatrix} d\xi d\eta + \frac{1}{2} \begin{vmatrix} x_{,\xi} & y_{,\xi} \\ x_{,\eta} & y_{,\eta} \end{vmatrix} d\xi d\eta$$

$$dA_{xy} = \underbrace{\begin{vmatrix} x_{,\xi} & y_{,\xi} \\ x_{,\eta} & y_{,\eta} \end{vmatrix}}_{|J^T(\xi_P, \eta_P; \underline{x}, \underline{y})|} dA_{\xi\eta} \quad (99)$$

$$\iint_{A_{xy}} g(x, y) dA_{xy} = \int_{-1}^1 \int_{-1}^1 g(x(\xi, \eta), y(\xi, \eta)) |J(\xi, \eta)| d\xi d\eta, \quad (100)$$

$$\iint_{A_{xy}} g(\underline{x}) dA_{xy} \approx \sum_{l=1}^{pq} g(\underline{x}(\underline{\xi}_l)) |J(\underline{\xi}_l)| w_l \quad (101)$$





$$\begin{bmatrix} X(\xi, \eta) \\ Y(\xi, \eta) \\ Z(\xi, \eta) \end{bmatrix} = \sum_{i=1}^n N_i(\xi, \eta) \begin{bmatrix} X_i \\ Y_i \\ Z_i \end{bmatrix}, \quad \begin{bmatrix} x(\xi, \eta) \\ y(\xi, \eta) \\ z(\xi, \eta) \end{bmatrix} = \sum_{i=1}^n N_i(\xi, \eta) \begin{bmatrix} x_i \\ y_i \\ z_i \end{bmatrix} \quad (102)$$

$$\begin{bmatrix} u(\xi, \eta) \\ v(\xi, \eta) \\ w(\xi, \eta) \end{bmatrix} = \sum_{i=1}^4 N_i(\xi, \eta) \begin{bmatrix} u_i \\ v_i \\ w_i \end{bmatrix} \quad (103)$$



$$\begin{bmatrix} \theta(\xi, \eta) \\ \phi(\xi, \eta) \\ \psi(\xi, \eta) \end{bmatrix} = \sum_{i=1}^4 N_i(\xi, \eta) \begin{bmatrix} \theta_i \\ \phi_i \\ \psi_i \end{bmatrix} \quad (104)$$

$$\begin{aligned} \underline{\mathbf{u}} &= \begin{bmatrix} \vdots \\ u_i \\ \vdots \end{bmatrix} & \underline{\mathbf{v}} &= \begin{bmatrix} \vdots \\ v_i \\ \vdots \end{bmatrix} & \underline{\mathbf{w}} &= \begin{bmatrix} \vdots \\ w_i \\ \vdots \end{bmatrix} \\ \underline{\boldsymbol{\theta}} &= \begin{bmatrix} \vdots \\ \theta_i \\ \vdots \end{bmatrix} & \underline{\boldsymbol{\phi}} &= \begin{bmatrix} \vdots \\ \phi_i \\ \vdots \end{bmatrix} & \underline{\boldsymbol{\psi}} &= \begin{bmatrix} \vdots \\ \psi_i \\ \vdots \end{bmatrix} \end{aligned}$$

$$\underline{\mathbf{d}}^\top = [\underline{\mathbf{u}}^\top \quad \underline{\mathbf{v}}^\top \quad \underline{\mathbf{w}}^\top \quad \underline{\boldsymbol{\theta}}^\top \quad \underline{\boldsymbol{\phi}}^\top \quad \underline{\boldsymbol{\psi}}^\top] \quad (105)$$

$$\begin{bmatrix} \frac{\partial u}{\partial x} \\ \frac{\partial u}{\partial y} \end{bmatrix} = \underbrace{(\underline{\mathbf{J}}')^{-1} \begin{bmatrix} \cdots & \frac{\partial N_i}{\partial \xi} & \cdots \\ \cdots & \frac{\partial N_i}{\partial \eta} & \cdots \end{bmatrix}}_{\underline{\mathbf{L}}(\xi, \eta; \underline{\mathbf{x}}_i) \text{ or just } \underline{\mathbf{L}}(\xi, \eta)} \begin{bmatrix} \vdots \\ u_i \\ \vdots \end{bmatrix} \quad (106)$$

$$\begin{bmatrix} \frac{\partial u}{\partial x} \\ \frac{\partial u}{\partial y} \\ \frac{\partial v}{\partial x} \\ \frac{\partial v}{\partial y} \end{bmatrix} = \underbrace{\begin{bmatrix} \underline{\mathbf{L}}(\xi, \eta) & 0 \\ 0 & \underline{\mathbf{L}}(\xi, \eta) \end{bmatrix}}_{\underline{\mathbf{Q}}(\xi, \eta)} \begin{bmatrix} \underline{\mathbf{u}} \\ \underline{\mathbf{v}} \end{bmatrix} \quad (107)$$



$$\begin{bmatrix} \frac{\partial\theta}{\partial x} \\ \frac{\partial\theta}{\partial y} \\ \frac{\partial\phi}{\partial x} \\ \frac{\partial\phi}{\partial y} \end{bmatrix} = \underline{\underline{Q}}(\xi, \eta) \begin{bmatrix} \underline{\theta} \\ \underline{\phi} \end{bmatrix} \quad (108)$$

$$\begin{bmatrix} e_x \\ e_y \\ g_{xy} \end{bmatrix} = \underbrace{\begin{bmatrix} +1 & 0 & 0 & 0 \\ 0 & 0 & 0 & +1 \\ 0 & +1 & +1 & 0 \end{bmatrix}}_{\underline{\underline{H}}'} \begin{bmatrix} \frac{\partial u}{\partial x} \\ \frac{\partial u}{\partial y} \\ \frac{\partial v}{\partial x} \\ \frac{\partial v}{\partial y} \end{bmatrix} = \underline{\underline{H}}' \underline{\underline{Q}}(\xi, \eta) \begin{bmatrix} \underline{u} \\ \underline{v} \end{bmatrix} \quad (109)$$

$$\begin{bmatrix} \kappa_x \\ \kappa_y \\ \kappa_{xy} \end{bmatrix} = \underbrace{\begin{bmatrix} 0 & 0 & +1 & 0 \\ 0 & -1 & 0 & 0 \\ -1 & 0 & 0 & +1 \end{bmatrix}}_{\underline{\underline{H}}''} \begin{bmatrix} \frac{\partial\theta}{\partial x} \\ \frac{\partial\theta}{\partial y} \\ \frac{\partial\phi}{\partial x} \\ \frac{\partial\phi}{\partial y} \end{bmatrix} = \underline{\underline{H}}'' \underline{\underline{Q}}(\xi, \eta) \begin{bmatrix} \underline{\theta} \\ \underline{\phi} \end{bmatrix} \quad (110)$$

$$\underline{e} = \underbrace{\begin{bmatrix} \underline{\underline{H}}' \underline{\underline{Q}}(\xi, \eta) & \underline{0} & \underline{0} & \underline{0} & \underline{0} \end{bmatrix}}_{\underline{\underline{B}}_e(\xi, \eta)} \underline{d} \quad (111)$$

$$\underline{\kappa} = \underbrace{\begin{bmatrix} \underline{0} & \underline{0} & \underline{0} & \underline{\underline{H}}'' \underline{\underline{Q}}(\xi, \eta) & \underline{0} \end{bmatrix}}_{\underline{\underline{B}}_\kappa(\xi, \eta)} \underline{d}. \quad (112)$$



$$\underline{\epsilon}(\xi, \eta, z) = (\underline{\underline{B}}_e(\xi, \eta) + z \underline{\underline{B}}_\kappa(\xi, \eta)) \underline{d}; \quad (113)$$

$$\begin{bmatrix} \bar{\gamma}_{zx} \\ \bar{\gamma}_{yz} \end{bmatrix} = \underline{\underline{L}}(\xi, \eta) \underline{\underline{w}} + \begin{bmatrix} 0 & +\underline{\underline{N}}(\xi, \eta) \\ -\underline{\underline{N}}(\xi, \eta) & 0 \end{bmatrix} \begin{bmatrix} \underline{\theta} \\ \underline{\phi} \end{bmatrix}, \quad (114)$$

$$\begin{bmatrix} \bar{\gamma}_{zx} \\ \bar{\gamma}_{yz} \end{bmatrix} = \underbrace{\begin{bmatrix} 0 & 0 & \underline{\underline{L}}(\xi, \eta) & 0 & \underline{\underline{N}}(\xi, \eta) & 0 \end{bmatrix}}_{\underline{\underline{B}}_\gamma(\xi, \eta)} \underline{d} \quad (115)$$

$$\underline{d}^\top = [\underline{u}^\top \quad \underline{v}^\top \quad \underline{w}^\top \quad \underline{\theta}^\top \quad \underline{\phi}^\top \quad \underline{\psi}^\top] \quad (116)$$

$$\underline{\underline{G}}^\top = [\underline{\underline{U}}^\top \quad \underline{\underline{V}}^\top \quad \underline{\underline{W}}^\top \quad \underline{\underline{\Theta}}^\top \quad \underline{\underline{\Phi}}^\top \quad \underline{\underline{\Psi}}^\top] \quad (117)$$



$$\delta \Upsilon_e = \delta \underline{d}^\top \underline{G}. \quad (118)$$

$$\underline{\sigma} = \underline{\underline{D}}(z) (\underline{\underline{B}}_e(\xi, \eta) + \underline{\underline{B}}_\kappa(\xi, \eta) z) \underline{d} \quad (119)$$

$$\delta \underline{\epsilon} = (\underline{\underline{B}}_e(\xi, \eta) + \underline{\underline{B}}_\kappa(\xi, \eta) z) \delta \underline{d} \quad (120)$$

$$\underline{q} = (\underline{\underline{a}} \underline{\underline{B}}_e(\xi, \eta) + \underline{\underline{b}} \underline{\underline{B}}_\kappa(\xi, \eta)) \underline{d} \quad (121)$$

$$\underline{m} = (\underline{\underline{b}}^\top \underline{\underline{B}}_e(\xi, \eta) + \underline{\underline{c}} \underline{\underline{B}}_\kappa(\xi, \eta)) \underline{d}, \quad (122)$$

$$\delta \underline{e} = \underline{\underline{B}}_e(\xi, \eta) \delta \underline{d} \quad (123)$$



$$\delta \underline{\kappa} = \underline{\underline{B}}_\kappa(\xi, \eta) \delta \underline{d}, \quad (124)$$



$$\begin{aligned} \delta \Upsilon_i^\dagger &= \iint_{\mathcal{A}} \int_h \delta \underline{\epsilon}^\top \underline{\sigma} dz d\mathcal{A} \\ &= \iint_{\mathcal{A}} \int_h ((\underline{\underline{B}}_e + \underline{\underline{B}}_\kappa z) \delta \underline{d})^\top \underline{\underline{D}} (\underline{\underline{B}}_e + \underline{\underline{B}}_\kappa z) \underline{d} dz d\mathcal{A} \\ &= \delta \underline{d}^\top \left[\iint_{\mathcal{A}} \int_h (\underline{\underline{B}}_e^\top + \underline{\underline{B}}_\kappa^\top z) \underline{\underline{D}} (\underline{\underline{B}}_e + \underline{\underline{B}}_\kappa z) dz d\mathcal{A} \right] \underline{d} \\ &= \delta \underline{d}^\top \underline{\underline{K}}^\dagger \underline{d}, \end{aligned} \quad (125)$$

$$\begin{aligned} \delta \Upsilon_i^\dagger &= \iint_{\mathcal{A}} (\delta \underline{e}^\top \underline{q} + \delta \underline{\kappa}^\top \underline{m}) d\mathcal{A} \\ &= \delta \underline{d}^\top \left[\iint_{\mathcal{A}} (\underline{\underline{B}}_e^\top (\underline{\underline{a}} \underline{\underline{B}}_e + \underline{\underline{b}} \underline{\underline{B}}_\kappa) + \underline{\underline{B}}_\kappa^\top (\underline{\underline{b}} \underline{\underline{B}}_e + \underline{\underline{c}} \underline{\underline{B}}_\kappa)) d\mathcal{A} \right] \underline{d} \\ &= \delta \underline{d}^\top \underline{\underline{K}}_\sigma \underline{d}, \end{aligned} \quad (126)$$

$$\{\underline{\underline{a}}, \underline{\underline{b}}, \underline{\underline{c}}\} = \int_h \underline{\underline{D}} \{1, z, z^2\} dz,$$

$$\begin{aligned} &\iint_{\Omega} g(\xi, \eta, x, y, z) d\Omega = \\ &= \int_{-1}^{+1} \int_{-1}^{+1} \int_{-\frac{h}{2}+o}^{+\frac{h}{2}+o} g(\xi, \eta, x(\xi, \eta), y(\xi, \eta), z) dz | \underline{\underline{J}}(\xi, \eta) | d\xi d\eta, \end{aligned} \quad (127)$$








$$\begin{aligned}
\delta \Upsilon_i^\ddagger &= \iint_{\mathcal{A}} \delta \underline{\gamma}_z^\top \underline{q}_z d\mathcal{A} \\
&= \delta \underline{d}^\top \left[h \iint_{\mathcal{A}} \underline{\underline{B}}_\gamma^\top \underline{\Gamma} \underline{\underline{B}}_\gamma d\mathcal{A} \right] \underline{d} \\
&= \delta \underline{d}^\top \underline{\underline{K}}^\ddagger \underline{d}.
\end{aligned} \tag{128}$$



$$\begin{aligned}
\delta \Upsilon_i &= \delta \Upsilon_i^\dagger + \delta \Upsilon_i^\ddagger \\
&= \delta \underline{d}^\top \left(\underline{\underline{K}}^\dagger + \underline{\underline{K}}^\ddagger \right) \underline{d} \\
&= \delta \underline{d}^\top \underline{\underline{K}} \underline{d}.
\end{aligned} \tag{129}$$

$$\delta \underline{d}^\top \underline{G} = \delta \Upsilon_e = \delta \Upsilon_i = \delta \underline{d}^\top \underline{\underline{K}} \underline{d}, \quad \forall \delta \underline{d}, \tag{130}$$

$$\underline{G} = \underline{\underline{K}} \underline{d}; \tag{131}$$







$$\underline{\underline{S}}(\xi, \eta, z) = \begin{bmatrix} \dots & \hat{u}_i(\xi, \eta, z) & \dots \\ \dots & \hat{v}_i(\xi, \eta, z) & \dots \\ \dots & \hat{w}_i(\xi, \eta, z) & \dots \end{bmatrix} \quad (132)$$

$$\underline{u}(\xi, \eta, z) = \underline{\underline{S}}(\xi, \eta, z) \underline{d}. \quad (133)$$

$$\dot{\underline{u}}(\xi, \eta, z) = \underline{\underline{S}}(\xi, \eta, z) \dot{\underline{d}} \quad (134)$$

$$E_{\text{kin}} = \frac{1}{2} \iiint_{\Omega} \dot{\underline{u}}^T \underline{u} \rho d\Omega \quad (135)$$

$$E_{\text{kin}} = \frac{1}{2} \iiint_{\Omega} \left[\underline{\underline{S}} \dot{\underline{d}} \right]^T \left[\underline{\underline{S}} \dot{\underline{d}} \right] \rho d\Omega, \quad (136)$$

$$E_{\text{kin}} = \frac{1}{2} \dot{\underline{d}}^T \left[\iiint_{\Omega} \underline{\underline{S}}^T \underline{\underline{S}} \rho d\Omega \right] \dot{\underline{d}} = \frac{1}{2} \dot{\underline{d}}^T \underline{\underline{\underline{M}}} \dot{\underline{d}}. \quad (137)$$

$$\underline{\underline{\underline{M}}} = \iiint_{\Omega} \underline{\underline{S}}^T \underline{\underline{S}} \rho d\Omega, \quad (138)$$


$$\begin{aligned} \dot{\underline{d}}^T \underline{G} &= \frac{dE_{\text{kin}}}{dt} = \frac{d}{dt} \left(\frac{1}{2} \dot{\underline{d}}^T \underline{\underline{\underline{M}}} \dot{\underline{d}} \right) \\ &= \frac{1}{2} \left(\ddot{\underline{d}}^T \underline{\underline{\underline{M}}} \dot{\underline{d}} + \dot{\underline{d}}^T \underline{\underline{\underline{M}}} \ddot{\underline{d}} \right) \\ &= \dot{\underline{d}}^T \underline{\underline{\underline{M}}} \ddot{\underline{d}}. \end{aligned}$$

$$\underline{G} = \underline{\underline{\underline{M}}} \ddot{\underline{d}} \quad (139)$$

$$\delta \underline{u}(\xi, \eta, z) = \underline{\underline{S}}(\xi, \eta, z) \delta \underline{d}, \quad (140)$$

$$\begin{aligned} \delta \underline{d}^T \underline{F} &= \iiint_{\Omega} (\delta \underline{u})^T \underline{p} d\Omega \\ &= \iiint_{\Omega} (\underline{\underline{S}} \delta \underline{d})^T \underline{p} d\Omega \\ &= \delta \underline{d}^T \iiint_{\Omega} \underline{\underline{S}}^T \underline{p} d\Omega, \end{aligned}$$

$$\underline{F} = \iiint_{\Omega} \underline{\underline{S}}^T \underline{p} d\Omega \quad (141)$$



$$\underline{G}_{ej} = \underline{\underline{K}}_{ej} \underline{d}_{ej} \quad (142)$$

$$\underline{d}_{gl} = \begin{bmatrix} u_{gl} \\ v_{gl} \\ w_{gl} \\ \theta_{gl} \\ \varphi_{gl} \\ \psi_{gl} \end{bmatrix}. \quad (143)$$

$$\underline{d}_g^\top = [\underline{d}_{g1}^\top \ \underline{d}_{g2}^\top \ \dots \ \underline{d}_{gl}^\top \ \dots \ \underline{d}_{gn}^\top] \quad (144)$$

$$\underline{F}_g^\top = [\underline{F}_{g1}^\top \ \underline{F}_{g2}^\top \ \dots \ \underline{F}_{gl}^\top \ \dots \ \underline{F}_{gn}^\top]; \quad (145)$$

$$\underline{R}_g^\top = [\underline{R}_{g1}^\top \ \underline{R}_{g2}^\top \ \dots \ \underline{R}_{gl}^\top \ \dots \ \underline{R}_{gn}^\top] \quad (146)$$

$$w_{e1n2} = \langle \hat{k}_{e1}, \hat{i}_{g2} \rangle u_{g2} + \langle \hat{k}_{e1}, \hat{j}_{g2} \rangle v_{g2} + \langle \hat{k}_{e1}, \hat{k}_{g2} \rangle w_{g2} \quad (147)$$

$$\theta_{e1n1} = \langle \hat{i}_{e1}, \hat{i}_{g1} \rangle \theta_{g1} + \langle \hat{i}_{e1}, \hat{j}_{g1} \rangle \phi_{g1} + \langle \hat{i}_{e1}, \hat{k}_{g1} \rangle \psi_{g1} \quad (148)$$

$$\begin{aligned} [\underline{\underline{P}}_{e1}]_{10,7} &= \langle \hat{k}_{e1}, \hat{i}_{g2} \rangle & [\underline{\underline{P}}_{e1}]_{13,4} &= \langle \hat{i}_{e1}, \hat{i}_{g1} \rangle \\ [\underline{\underline{P}}_{e1}]_{10,8} &= \langle \hat{k}_{e1}, \hat{j}_{g2} \rangle & [\underline{\underline{P}}_{e1}]_{13,5} &= \langle \hat{i}_{e1}, \hat{j}_{g1} \rangle \\ [\underline{\underline{P}}_{e1}]_{10,9} &= \langle \hat{k}_{e1}, \hat{k}_{g2} \rangle & [\underline{\underline{P}}_{e1}]_{13,6} &= \langle \hat{i}_{e1}, \hat{k}_{g1} \rangle, \end{aligned}$$

node	X	Y	Z
g1	$-ac$	0	$+a$
g2	0	$+as$	$+a$
g3	$+ac$	0	$+a$
g4	$-ac$	0	0
g5	0	$+as$	0
g6	$+ac$	0	0
g7	$-ac$	0	$-a$
g8	0	$+as$	$-a$
g9	$+ac$	0	$-a$

	u_{ni}	v_{ni}	w_{ni}	θ_{ni}	φ_{ni}	ψ_{ni}
U_{ni}						
V_{ni}						
W_{ni}						
Θ_{ni}						
Φ_{ni}						
Ψ_{ni}						
$i = 1 \dots 4$						

	n1	n2	n3	n4
e1	g1	g2	g5	g4
e2	g2	g3	g6	g5
e3	g4	g5	g8	g7
e4	g5	g6	g9	g8

\underline{P}_{e1}	\underline{d}_{g1}	\underline{d}_{g2}	\underline{d}_{g3}	\underline{d}_{g4}	\underline{d}_{g5}	\underline{d}_{g6}	\underline{d}_{g7}	\underline{d}_{g8}	\underline{d}_{g9}
u_{e1ni}	■				■				
v_{e1ni}		■				■			
w_{e1ni}	■				■				
θ_{e1ni}		■			■				
φ_{e1ni}		■			■		■		
ψ_{e1ni}		■		■		■			


\underline{P}_{e2}	\underline{d}_{g1}	\underline{d}_{g2}	\underline{d}_{g3}	\underline{d}_{g4}	\underline{d}_{g5}	\underline{d}_{g6}	\underline{d}_{g7}	\underline{d}_{g8}	\underline{d}_{g9}
u_{e2ni}		■	■						
v_{e2ni}		■		■					
w_{e2ni}		■	■			■			
θ_{e2ni}		■	■			■			
φ_{e2ni}			■			■			
ψ_{e2ni}		■	■			■			

\underline{P}_{e3}	\underline{d}_{g1}	\underline{d}_{g2}	\underline{d}_{g3}	\underline{d}_{g4}	\underline{d}_{g5}	\underline{d}_{g6}	\underline{d}_{g7}	\underline{d}_{g8}	\underline{d}_{g9}
u_{e3ni}				■	■			■	
v_{e3ni}				■		■			
w_{e3ni}			■	■			■		
θ_{e3ni}				■	■			■	
φ_{e3ni}				■		■		■	
ψ_{e3ni}				■	■		■	■	


\underline{P}_{e4}	\underline{d}_{g1}	\underline{d}_{g2}	\underline{d}_{g3}	\underline{d}_{g4}	\underline{d}_{g5}	\underline{d}_{g6}	\underline{d}_{g7}	\underline{d}_{g8}	\underline{d}_{g9}
u_{e4ni}					■	■		■	
v_{e4ni}					■		■		
w_{e4ni}				■	■				
θ_{e4ni}					■	■			
φ_{e4ni}					■		■		
ψ_{e4ni}					■	■		■	

	d_{g1}	d_{g2}	d_{g3}	d_{g4}	d_{g5}	d_{g6}	d_{g7}	d_{g8}	d_{g9}
F_{g1}									
F_{g2}									
F_{g3}									
F_{g4}									
F_{g5}									
F_{g6}									
F_{g7}									
F_{g8}									
F_{g9}									


(a)



(b)



(c)



(d)

$$\underline{d}_{ej} = \underline{\underline{P}}_{ej} \underline{d}_g, \quad \forall j. \quad (149)$$



$$\underline{G}_{ej} = \underline{\underline{K}}_{ej} \underline{\underline{P}}_{ej} \underline{d}_g, \quad \forall j; \quad (150)$$

$$\delta \underline{d}_g^\top \underline{G}_{g \leftarrow ej} = (\underline{\underline{P}}_{ej} \delta \underline{d}_g)^\top \underline{G}_{ej}, \quad \forall \delta \underline{d}_g \quad (151)$$

$$\underline{G}_{g \leftarrow ej} = \underline{\underline{P}}_{ej}^\top \underline{G}_{ej} \quad (152)$$

$$\underline{G}_{g \leftarrow ej} = \underline{\underline{P}}_{ej}^\top \underline{\underline{K}}_{ej} \underline{\underline{P}}_{ej} \underline{d}_g; \quad (153)$$



$$\underline{G}_g = \sum_j \underline{G}_{g \leftarrow ej} = \left(\sum_j \underbrace{\underline{\underline{P}}_{ej}^\top \underline{\underline{K}}_{ej} \underline{\underline{P}}_{ej}}_{\underline{\underline{K}}_{g \leftarrow ej}} \right) \underline{d}_g = \underline{\underline{K}}_g \underline{d}_g, \quad (154)$$





$$b_{ej} = (i_{\max} - i_{\min} + 1) l, \quad (155)$$

$$b = \max_{ej} b_{ej} \quad (156)$$

$$\underline{F}_g = \sum_j \underline{\underline{P}}_{ej}^\top \underline{F}_{ej}; \quad (157)$$





$$\sum_i \alpha_{ji} d_i = \underline{\alpha}_j^\top \underline{d} = \beta_j$$



$$\begin{aligned}\underline{\alpha}_I^\top &= [3 \ 0 \ 1] & \beta_I &= 0 \\ \underline{\alpha}_{II}^\top &= [0 \ 1 \ 0] & \beta_{II} &= 0.2\end{aligned}$$

$$\sum_i \alpha_{ji} d_i = \underline{\alpha}_j^\top \underline{d} = \beta_j, \quad j = 1 \dots m \quad (158)$$

$$\underline{\mathcal{L}}^\top \underline{d} = \underline{\beta}. \quad (159)$$

$$\underline{\mathcal{L}}^\top \delta \underline{d} = \underline{0}, \quad (160)$$

$$\underline{R} = -\underline{\mathcal{L}} \ell, \quad (161)$$



$$\underline{\mathbf{R}}^j = - \begin{bmatrix} \vdots \\ \alpha_{ji} \\ \vdots \end{bmatrix} \ell_j \quad (162)$$

$$\underline{\mathbf{K}} \underline{\mathbf{d}} = \underline{\mathbf{F}} + \underline{\mathbf{R}}. \quad (163)$$

$$\underline{\underline{\mathbf{L}}} \underline{\mathbf{d}} + \underline{\underline{\mathbf{L}}} \underline{\ell} = \underline{\mathbf{F}}$$

$$\begin{bmatrix} \underline{\mathbf{K}} & \underline{\underline{\mathbf{L}}} \\ \underline{\underline{\mathbf{L}}}^\top & \underline{\mathbf{0}} \end{bmatrix} \begin{bmatrix} \underline{\mathbf{d}} \\ \underline{\ell} \end{bmatrix} = \begin{bmatrix} \underline{\mathbf{F}} \\ \underline{\beta} \end{bmatrix}, \quad (164)$$

$$\frac{1}{2} \underline{\mathbf{d}}^\top \underline{\underline{\mathbf{L}}} \underline{\mathbf{d}} - \underline{\mathbf{d}}^\top \underline{\mathbf{F}} + \underline{\ell}^\top (\underline{\underline{\mathbf{L}}}^\top \underline{\mathbf{d}} - \underline{\beta}), \quad (165)$$

$$\frac{1}{2} \underline{\mathbf{d}}^\top \underline{\underline{\mathbf{L}}} \underline{\mathbf{d}} - \underline{\mathbf{d}}^\top \underline{\mathbf{F}}$$

$$\underline{\underline{\mathbf{L}}}^\top \underline{\mathbf{d}} - \underline{\beta} = \underline{\mathbf{0}}$$

$$\underline{\mathbf{R}} = -\underline{\underline{\mathbf{L}}} \underline{\ell}^*.$$

$$d_k = \sum_{i \neq k} \left(-\frac{\alpha_{ji}}{\alpha_{jk}} \right) d_i + \left(\frac{\beta_j}{\alpha_{jk}} \right), \quad j = 1 \dots m \quad (166)$$



$$\begin{bmatrix} \underline{\mathbf{r}} \\ \underline{\mathbf{t}} \end{bmatrix} = \underbrace{\begin{bmatrix} \underline{\mathbf{E}}_R \\ \underline{\mathbf{E}}_T \end{bmatrix}}_{\underline{\mathbf{E}}} \underline{\mathbf{d}} \quad \underline{\mathbf{d}} = \underbrace{\begin{bmatrix} \underline{\mathbf{E}}_R^\top & \underline{\mathbf{E}}_T^\top \end{bmatrix}}_{\underline{\mathbf{E}}^\top \equiv \underline{\mathbf{E}}^{-1}} \begin{bmatrix} \underline{\mathbf{r}} \\ \underline{\mathbf{t}} \end{bmatrix},$$

$$\underline{\mathbf{r}} = \underline{\mathbf{E}}_R \underline{\mathbf{d}} \quad \underline{\mathbf{t}} = \underline{\mathbf{E}}_T \underline{\mathbf{d}},$$

$$t_j = \sum_{h=1}^{n-m} \lambda_{jh} r_h + \delta_j, \quad j = 1 \dots m \quad (167)$$

$$\underline{\mathbf{t}} = \underline{\lambda} \underline{\mathbf{r}} + \underline{\delta}, \quad (168)$$

$$\begin{aligned} \underline{\mathbf{d}} &= \left(\underline{\mathbf{E}}^\top \begin{bmatrix} \underline{\mathbf{I}} \\ \underline{\bar{\lambda}} \end{bmatrix} \right) \underline{\mathbf{r}} + \left(\underline{\mathbf{E}}^\top \begin{bmatrix} \underline{0} \\ \underline{\delta} \end{bmatrix} \right) \\ &= \underline{\Lambda} \underline{\mathbf{r}} + \underline{\Delta}; \end{aligned} \quad (169)$$



The diagram illustrates the decomposition of a vector \underline{d} into three components: retained, tied, and general degrees of freedom. On the left, a table lists conditions for each type of degree of freedom:

retained dof.	d_i	i	$\cdot \cdot \cdot 1 \cdot \cdot \cdot 0 \cdot \cdot$	\cdot
$d_i = r_h$	\vdots			0
tied dof.	d_k	k	$\cdot \cdot \lambda_{kh} = 0 \cdot \cdot$	r_h
fix. disp. kind	\vdots	$=$		\cdot
$d_k = a$	\vdots			\cdot
tied dof.	d_k	k	$\cdot \cdot \lambda_{kh} \cdot \cdot \cdot \cdot$	$\Delta_k = a$
general	\vdots			Δ_k

Below the table, the decomposition is shown as:

$$\underline{d} = \underline{\Lambda} \underline{r} + \underline{\Delta}$$

$$\delta \underline{d} = \underline{\Lambda} \delta \underline{r} = \underline{\Lambda}_1 \delta r_1 + \underline{\Lambda}_2 \delta r_2 + \dots + \underline{\Lambda}_{n-m} \delta r_{n-m} \quad (170)$$

$$\langle \underline{\Lambda}_h, \underline{R} \rangle = 0 \quad h = 1 \dots n - m, \quad (171)$$

or, equivalently,

$$\underline{\Lambda}^\top \underline{R} = \underline{0}. \quad (172)$$

$$\underline{\underline{K}} (\underline{\Lambda} \underline{r} + \underline{\Delta}) = \underline{\underline{F}} + \underline{\underline{R}} \quad (173)$$

$$\underline{\underline{K}} \underline{\Lambda} \underline{r} = (\underline{\underline{F}} - \underline{\underline{K}} \underline{\Delta}) + \underline{\underline{R}}, \quad (174)$$

$$\underbrace{\underline{\Lambda}^\top \underline{\underline{K}} \underline{\Lambda}}_{\underline{\underline{K}}_R} \underline{r} = \underbrace{\underline{\Lambda}^\top (\underline{\underline{F}} - \underline{\underline{K}} \underline{\Delta})}_{\underline{\underline{F}}_R} + \underbrace{\underline{\Lambda}^\top \underline{\underline{R}}}_{=0}, \quad (175)$$

$$\underline{\underline{K}}_R \underline{r} = \underline{\underline{F}}_R \quad (176)$$

$$\underline{d}^* = \underline{\Lambda} \underline{r}^* + \underline{\Delta}; \quad (177)$$



$$\underline{R}^* = \underline{\underline{K}} (\underline{\Lambda} \underline{r}^* + \underline{\Delta}) - \underline{\underline{F}}. \quad (178)$$

$$\underline{d}_{ej}^* = \underline{\underline{P}}_{ej} \underline{d}^*. \quad (179)$$

$$\underline{e} = \underline{\underline{B}}_{ej}^e(\xi, \eta) \underline{d}_{ej}^* \quad \underline{\kappa} = \underline{\underline{B}}_{ej}^\kappa(\xi, \eta) \underline{d}_{ej}^* \quad (180)$$

$$\underline{\varepsilon} = (\underline{\underline{B}}_{ej}^e(\xi, \eta) + \underline{\underline{B}}_{ej}^\kappa(\xi, \eta) z) \underline{d}_{ej}^*. \quad (181)$$



$$\underline{\gamma} z = \underline{\underline{B}}_{ej}^\gamma(\xi, \eta) \underline{d}_{ej}^*. \quad (182)$$



$$\begin{bmatrix} u_i \\ v_i \\ w_i \\ \theta_i \\ \phi_i \\ \psi_i \end{bmatrix} = \underbrace{\begin{bmatrix} 1 & 0 & 0 & 0 & +(z_i - z_C) & -(y_i - y_C) \\ 0 & 1 & 0 & -(z_i - z_C) & 0 & +(x_i - x_C) \\ 0 & 0 & 1 & +(y_i - y_C) & -(x_i - x_C) & 0 \\ 0 & 0 & 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 0 & 0 & 1 \end{bmatrix}}_{\underline{\underline{L}}_i} \cdot \begin{bmatrix} u_C \\ v_C \\ w_C \\ \theta_C \\ \phi_C \\ \psi_C \end{bmatrix}. \quad (183)$$

$$\begin{bmatrix} U_i \\ V_i \\ W_i \end{bmatrix} = q_i \left(\begin{bmatrix} a \\ b \\ c \end{bmatrix} + \begin{bmatrix} 0 & d & -f \\ -d & 0 & e \\ f & -e & 0 \end{bmatrix} \begin{bmatrix} x_i \\ y_i \\ z_i \end{bmatrix} \right), \quad (184)$$

$$\begin{bmatrix} U_C \\ V_C \\ W_C \end{bmatrix} = \sum_i \begin{bmatrix} U_i \\ V_i \\ W_i \end{bmatrix}, \quad \begin{bmatrix} \Theta_C \\ \Phi_C \\ \Psi_C \end{bmatrix} = \sum_i \begin{bmatrix} U_i \\ V_i \\ W_i \end{bmatrix} \wedge \begin{bmatrix} x_i - x_C \\ y_i - y_C \\ z_i - z_C \end{bmatrix} \quad (185)$$





$$\underline{\mathbf{K}} \underline{\mathbf{d}} = \underline{\mathbf{F}}, \quad (186)$$

$$\ddot{\underline{\mathbf{d}}} = \underbrace{\begin{bmatrix} \cdots & \underline{\mathbf{t}}_l & \cdots \end{bmatrix}}_{\underline{\mathbf{T}}} \underbrace{\begin{bmatrix} \vdots \\ \alpha_l \\ \vdots \end{bmatrix}}_{\underline{\alpha}}, \quad (187)$$

$$\underline{\mathbf{T}}^\top \underline{\mathbf{M}} \underline{\mathbf{T}} \underline{\alpha} = \underline{\mathbf{T}}^\top \underline{\mathbf{F}} \quad (188)$$

$$\underline{\mathbf{M}} \underline{\mathbf{T}} \underline{\alpha} = \underline{\mathbf{F}} [+ \underline{\mathbf{R}}_l]$$

$$\underline{\mathbf{K}} \underline{\mathbf{d}} = \underline{\mathbf{F}} - \underline{\mathbf{M}} \underline{\mathbf{T}} \underline{\alpha}, \quad (189)$$



$$\underline{\underline{M}} \ddot{\underline{d}} + \underline{\underline{C}} \dot{\underline{d}} + \underline{\underline{K}} \underline{d} = \underline{f}(t), \quad \underline{d} = \underline{d}(t) \quad (190)$$

$$\underline{f}(t) = \frac{\bar{\underline{f}} e^{j\omega t} + \bar{\underline{f}}^* e^{-j\omega t}}{2} = \text{Re}(\bar{\underline{f}} e^{j\omega t}) \quad (191)$$

$$\underline{f}(t) = \bar{\underline{f}} e^{j\omega t} \quad (192)$$

$$\text{Re}(\bar{\underline{f}} e^{j\omega t}) = \text{Re}(\bar{\underline{f}}) \cos \omega t - \text{Im}(\bar{\underline{f}}) \sin \omega t \quad (193)$$

$$\underline{d}(t) = \bar{\underline{d}} e^{j\omega t} \quad (194)$$

$$(-\omega^2 \underline{\underline{M}} + j\omega \underline{\underline{C}} + \underline{\underline{K}}) \bar{\underline{d}} = \bar{\underline{f}} \quad (195)$$

$$(-\omega^2 \underline{\underline{M}} + \underline{\underline{K}}) \bar{\underline{d}} = \underline{0} \quad (196)$$

$$(\underline{\underline{M}}^{-1} \underline{\underline{K}} - \omega^2 \underline{\underline{I}}) \hat{\underline{d}} = \underline{0}; \quad (197)$$

$$m_i = \hat{\underline{d}}_i^\top \underline{\underline{M}} \hat{\underline{d}}_i = 1 \quad (198)$$

$$\underline{x}(t) = a \hat{\underline{d}}_i \sin(\omega_i t) \quad (199)$$

$$f(t) = \hat{\underline{f}} \cos(\omega_i t), \quad (200)$$

$$\underbrace{(-\omega_i^2 \underline{\underline{M}} + \underline{\underline{K}})}_{=0} \hat{\underline{d}}_i a_i \sin(\omega_i t) + \omega_i a_i \underline{\underline{C}} \hat{\underline{d}}_i \cos(\omega_i t) = \bar{\underline{f}} \cos(\omega_i t). \quad (201)$$

$$a_i = \frac{\hat{\underline{d}}_i^\top \bar{\underline{f}}}{\omega_i \hat{\underline{d}}_i^\top \underline{\underline{C}} \hat{\underline{d}}_i} \quad (202)$$

$$\hat{\underline{d}}_j^\top \underline{\underline{M}} \hat{\underline{d}}_i = m_i \delta_{ij} \quad \hat{\underline{d}}_j^\top \underline{\underline{K}} \hat{\underline{d}}_i = m_i \omega_i^2 \delta_{ij} \quad (203)$$

$$\underline{\Xi} = [\hat{\underline{d}}_1 \quad \cdots \quad \hat{\underline{d}}_l \quad \cdots \quad \hat{\underline{d}}_m], \quad (204)$$



$$\bar{\underline{d}} = \underline{\Xi} \bar{\underline{\xi}} \quad (205)$$



$$\underline{\Xi}^\top \underline{\underline{M}} \underline{\Xi} = \underline{\underline{I}} \quad \underline{\Xi}^\top \underline{\underline{K}} \underline{\Xi} = \underline{\underline{\Omega}} = \text{diag}(\omega_l^2); \quad (206)$$

$$\underline{\underline{C}} = \alpha \underline{\underline{M}} + \beta \underline{\underline{K}} \quad (207)$$

$$\underline{\Xi}^\top (-\omega^2 \underline{\underline{M}} + j\omega \underline{\underline{C}} + \underline{\underline{K}}) \underline{\Xi} \bar{\underline{\xi}} = \underline{\Xi}^\top \bar{\underline{f}} \quad (208)$$

$$(-\omega^2 \underline{\underline{I}} + j\omega (\alpha \underline{\underline{I}} + \beta \underline{\underline{\Omega}}) + \underline{\underline{\Omega}}) \bar{\underline{\xi}} = \underline{\Xi}^\top \bar{\underline{f}}, \quad (209)$$





$$(-\omega^2 + j\omega (\alpha + \beta\omega_l^2) + \omega_l^2) \xi_l = q_l, \quad j = 1 \dots m \quad (210)$$

$$\begin{aligned} \xi_l(t) &= \operatorname{Re}(\bar{\xi}_l) \cos \omega t - \operatorname{Im}(\bar{\xi}_l) \sin \omega t \\ &= |\bar{\xi}_l| \cos(\omega t + \psi_l - \phi_l) \end{aligned}$$



$$a_l = 1 - r_l^2 \quad b_l = 2\zeta_l r_l \quad r_l = \frac{\omega}{\omega_l}$$


$$|\bar{\xi}_l| = \frac{|\bar{q}_l|}{\omega_l^2} \frac{1}{\sqrt{a_l^2 + b_l^2}}$$

$$\psi_l = \arg(\bar{q}_l)$$

$$\phi_l = \arg(a_l + jb_l)$$

$$\begin{aligned} \operatorname{Re}(\bar{\xi}_l) &= \frac{1}{\omega_l^2} \frac{a_l \operatorname{Re}(\bar{q}_l) + b_l \operatorname{Im}(\bar{q}_l)}{a_l^2 + b_l^2} \\ \operatorname{Im}(\bar{\xi}_l) &= \frac{1}{\omega_l^2} \frac{a_l \operatorname{Im}(\bar{q}_l) - b_l \operatorname{Re}(\bar{q}_l)}{a_l^2 + b_l^2}. \end{aligned}$$





$$\begin{aligned}
 \delta U_i &= \iiint_V \delta \underline{\epsilon}^\top (\underline{\sigma}_0 + \underline{\underline{D}} \underline{\epsilon}) dV \\
 &= \iiint_V [\underline{\underline{B}}(\underline{d}) \delta \underline{d}]^\top (\underline{\sigma}_0 + \underline{\underline{D}} \underline{\underline{B}}(\underline{d}) \underline{d}) dV \\
 &= \dots \\
 &= \delta \underline{d} ((\underline{\underline{K}}_{ej}^M + \underline{\underline{K}}_{ej}^G) \underline{d} + o(\underline{d})) .
 \end{aligned}$$

$$(\underline{\underline{K}}^M + \lambda \underline{\underline{K}}^G) \delta \underline{d} = \delta \underline{F} \quad (211)$$

$$(\underline{\underline{K}}^M + \lambda_i \underline{\underline{K}}^G) \delta \hat{d}_i = 0 \quad (212)$$

Bibliography

- [1] A. E. H. Love, *A treatise on the mathematical theory of elasticity*. Cambridge university press, 2013.